


## Wireless Brightness Remote Controller



## Features and Benefits

- Use RF signal for telecontroller, free and easy operation, no direction in 20 meters;
- Use your finger to touch the color ring, you can change the brightness from the highest to the lowest (100%-1%, 50 grades to adjust)
- Long life, lifespan up to 40000 hours;
- Low energy consumption;
- No UV radiation, no stroboflash;
- Accord with European Union CE, RoHS directive.

## Technical Parameters

- Input Voltage: DC12V, DC24V (optional)
- Connection type: Common anode
- Radio frequency: 433.92MHz
- Receiver sensitivity: -105dbm
- Radio receive way: ASK
- Max STDBY current: 10mA
- Max load: 6A (each circuit)
- Control mode: PWM
- Control way: 2 ways, respectively corresponding WW, CW two color temperature
- Static power consumption: 30LED/M:  $\leq 5.4W$  60LED/M:  $\leq 10.8W$
- Static current: 30LED/M: 450mA 60LED/M: 900mA
- Working temp: -20~80 degrees
- Material: Controller: aluminum remote: ABS+PC
- Life span: 40,000hrs
- Telecontrol distance: 20m
- No UV radiation, no stroboflash
- Safety Assurance: CE, RoHS
- Max no. of memory telecontroller: 6pcs

## Code & Reference


**20500003**

**RF Wireless Touching LED Brightness Remote Controller**

## Warranty


2 years

## Dimension



## Function of Keys

1. Key 1: on
2. Key 2: off
3. Key 3: highest brightness
4. Key 4: medium brightness
5. Key 5: lowest brightness




## How to use

1. Use your finger to touch the color ring ,you can change the brightness from the highest to the lowest (100%-1%,50 grades to adjust).
2. Resume fuction. The previous settings will be resumed while power on again.
3. Matching code:  
Press Key 3 once within 3 seconds when power on again, the light will blink 3 times if matching is successful.
4. Clearing code:  
Press Key 3 five times within 3 seconds when power on again, the light will blink 6 times if clearing is successful.

### Caution:

Please don't touch or press the color ring while loading the batteries to protect the sensitiveness. Please use the remote controller 3 seconds after the batteries are loaded. Please reload the batteries when you find the color ring is not sensitive.

## Connecting Chart



## Packing

- Size: Remote: L85\*W65\*H24mm Controller: 65\*38\*25mm
- Packing: 8x7.5x13cm/set
- G.W.: 0.156kgs/set



Qty: 1PC  
Size: 120\*70\*50mm  
GW: 156g

